

## Amptown Controlite Washlight (Halogen) (WL-HX Squarcle)

10/99

Kanal	Name	DMX	%	hex	Funktion
1	Dimmer	0	0%	00 h	Helligkeit 0%
		255	100%	FF h	Helligkeit 100%
2	Fokus	0	0%	00 h	Flood - Abstrahlwinkel 36°
		255	100%	FF h	Spot - Abstrahlwinkel 9°
3	Bewegung horizontal (grob) pan ( X )	0	0%	00 h	Horizontal -170°
		127	50%	7F h	Horizontal 0°
		255	100%	FF h	Horizontal +170°
4	Bewegung horizontal (fein) pan ( X )	0	0%	00 h	
		127	50%	7F h	
		255	100%	FF h	
5	Bewegung vertikal (grob) tilt ( Y )	0	0%	00 h	Vertikal -135°
		127	50%	7F h	Vertikal 0°
		255	100%	FF h	Vertikal +135°
6	Bewegung vertikal (fein) tilt ( Y )	0	0%	00 h	
		127	50%	7F h	
		255	100%	FF h	
7	Gelb stufenlos	0	0,0%	00 h	Kein Gelb (Weiß)
		220	86,3%	DC h	Volles Gelb
8	Magenta stufenlos	0	0,0%	00 h	Kein Magenta (Weiß)
		220	86,3%	DC h	Volles Magenta
9	Cyan stufenlos	0	0,0%	00 h	Kein Cyan (Weiß)
		220	86,3%	DC h	Volles Cyan

## Amptown Controlite Washlight (Halogen) (WL-HX Squarcle)

10/99

Kanal	Name	DMX	%	hex	Funktion
10	Sonderkanal:	0...201	0...79%	00...C9 h	Normalbetrieb
	RESET	202	79,2%	CA h	RESET - Servo
		203	79,6%	CB h	RESET - Servo + Stepper
		204	80,0%	CC h	RESET - Stepper
		205...255	81...100%	CD...FF h	Normalbetrieb
11	Blende Drehung	0	0%	00 h	
		255	100%	FF h	
12	Blende 1	0	0%	00 h	Blenden offen
		255	100%	FF h	Blenden geschlossen
13	Blende 2	0	0%	00 h	Blenden offen
		255	100%	FF h	Blenden geschlossen
14	Blende 3	0	0%	00 h	Blende offen
		255	100%	FF h	Blende geschlossen
15	Blende 4	0	0%	00 h	Blende offen
		255	100%	FF h	Blende geschlossen